

# KOHLER®



## DIESEL 4000 E XL C5

PORTABLE POWER

GENERATING SET Range DIESEL

### PRODUCT ADVANTAGES

Generating set guaranteed 3 years  
KOHLER air-cooled industrial engine  
Large Autonomy  
Comfort of prehension thanks to the ergonomic handles  
Electric starter with batteries without maintenance

GENERATOR SMART CARE is a Bluetooth box which can be used on all the brand's portable generators.

TECHNOLOGY EQUIPPED WITH AN INNOVATIVE APPLICATION Generator Smart Care is a digital solution which provides access to:

- The list of generators
- The maintenance due dates
- A maintenance aid
- The map of reseller partners

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

### Range DIESEL

Both long run times and very long life for professional applications.

## DIESEL 4000 E XL C5

### GENERAL SPECIFICATIONS

Range	DIESEL
Frequency (Hz)	50 Hz
Max power (kW)	3.4
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Diesel Fuel
Tank (L)	16
75% cons. (l/h)	0.9
75% Autonomy (h)	17.8
Sound power level guaranteed LwA dB(A)	108
Acoustic pressure level @1m in dB(A)	92
Acoustic pressure level @7m in dB(A)	78

### ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine ref.	KD350E_C5
Engine Type	Diesel O.H.V.
Start	Electrical
Oil shutdown	Oui
Displacement (cm <sup>3</sup> )	349
Oil system capacity including filters (l)	1.2

### ALTERNATOR SPECIFICATION

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	81
Width (cm)	55.5
Height (cm)	59
Dry Weight (kg)	84

### PACKAGING

Packaging type	Box
Length (cm)	82
Width (cm)	56.5
Height (cm)	60
Weight (kg)	87
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	193
weight of the packaged Pallet (kg)	532

STAGE V



KOHLER®

\$DATEJOURS

DIESEL 4000 E XL C5 - PORTABLE POWER – GENERATING SET DIESEL

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 – France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com



### ACCESSORIES SUPPLIED

User and maintenance manual  
Floor maintaining slot  
Ergonomic handle grip

### OPTIONS

- R01** This set includes the hour meter and the differential circuit breaker
- R05M** The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut
- 0**
- 3499231001745** RKDS1 - Maintenance kit for KOHLER CH350E and CH440E engines (Diesel 6000 E XL C - Diesel 6500 TE XL C)
- RH1** Cover for SDMO 's generating sets, welding sets and water pumps
- RPM** Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
- RPQ** For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm<sup>2</sup> cable
- RBAC** Removable storage box
- RKD1** kit of two differential removable adapters for domestic sockets. Schema for ground bonding with isolated neutral